logitech®



DATA SHEET

LOGITECH ROOMMATE

Turn any space into an appliance-based video conferencing room with RoomMate, an appliance purpose-built for video collaboration. RoomMate runs CollabOS, the unifying operating system within Logitech's video bar appliances, providing a simple, consistent deployment across all meeting rooms.

COLLABOS APPLIANCE FOR SUPPORTED CONFERENCE CAMERAS AND ROOM SOLUTION PERIPHERALS

By connecting RoomMate with MeetUp or a Rally System, IT can deploy Microsoft Teams Rooms on Android, Zoom Rooms Appliances, or other video conferencing solutions in any meeting space. For rooms with custom audio systems, RoomMate is compatible with select partners like Biamp, QSC, and Shure.

RoomMate is built for deployment and management at scale. In a low-profile form factor, RoomMate delivers all the capabilities needed for HD video conferencing with one or two displays and can be mounted securely and out of sight. Easily monitor and manage RoomMate together with other devices through Logitech Sync, Teams admin center, or Zoom Device Management.





Logitech RoomMate shown with Rally Plus system

PURPOSE-BUILT FOR VIDEO COLLABORATION

RoomMate runs CollabOS, which allows you to easily deploy Microsoft Teams Rooms on Android, Zoom Rooms Appliances, and other leading video conferencing services.









MODULAR VERSATILITY

Turn any space into an appliancebased video conferencing room. Connect the modular Rally System or MeetUp to RoomMate and add a Logitech Tap touch controller, Scribe whiteboard camera,* and other collaboration devices to your meeting rooms.



POWER, WITH CONNECTIONS

In a sleek, low-profile form factor, RoomMate delivers all the power you need for HD video conferencing in rooms with one or two displays.



FLEXIBLE, NEAT, SECURE

Mount RoomMate securely and out of sight. The optional Compute Mount supports discreet installation and cable retention behind displays, inside cabinets, and under tables.

^{*}Scribe compatibility may vary, see www.logitech.com/support/scribe-compatibility for the latest information.

VERIFIED AUDIO PARTNERS

Use the audio system of your choice. Default to the conference camera's audio when you pair RoomMate with MeetUp or Rally System. Or choose a verified audio system from select partners when RoomMate is used alongside Rally Camera.









SIMPLE TO MANAGE

Easily manage your Logitech video collaboration devices with Logitech Sync. Monitor room health, deploy updates, and modify settings all from a single cloud-based platform. And with Sync Insights, you can see how meeting spaces are utilized over time.



PURPOSE-BUILT FOR VIDEO COLLABORATION

Deploy video collaboration solutions at scale with CollabOS, the secure operating system powering Logitech appliances and select devices.



GENERAL		INTERFACES
Appliance Mode: Supports Microsoft Teams Rooms on Android, Zoom Rooms, RingCentral Rooms. For the latest information on certifications and compatibility, visit www.logitech.com/support/vc-certifications. Certified Hardware: Supports Logitech MeetUp, Rally Camera, Rally System, Rally Plus System, Tap, Tap IP Verified Hardware: Supports Biamp TesiraFORTÉ X 400, QSC Q-SYS Core 8 Flex, Shure IntelliMix P300. For latest information on compatible products, contact your preferred partner. Network Protocol Support: IPv4, IPv6 Proxy Support: IP based Proxy, FQDN based Proxy, Proxy using PAC file		
PACKAGE CONTENTS	DIMENSIONS	
Logitech RoomMate Mounting plate Power supply Remote control AC cable User documentation	Height: 34.5 mm (1.36 in) Width: 161 mm (6.34 in) Depth: 211 mm (8.31 in)	
POWER & CABLES	SECURITY	
Power Supply: Auto-sensing Operating Voltage/Power: 100-240V, 19V, 4.74A Power Supply Dimensions: 127 mm x 51 mm x 30 mm DC Cable: 1.5 m/4.9 ft AC Cable: 1 m/3.28 ft	Full Disk Encryption: AES-128 Data Encryption: Symmetric Keys, PKI Device Identity: Protected by device attestation Device Access: Authenticated using API Key Protection: Arm TrustZone, RPMP Device Security: Kensington Lock	
SOFTWARE	ENVIRONMENTAL	
Operating System: Logitech CollabOS 1.4 or higher Device Management: Logitech Sync and supported device management platforms	Operating Temperature: 0 to 40 °C Storage Temperature: -40 to 70 °C Humidity: 10 to 95%	
WARRANTY	PART NUMBERS	
Standard: two-year limited hardware warranty included Extended: Additional one-year and three-year extended warranties available at the time of hardware purchase. Contact your reseller for availability.	Logitech RoomMate: 950-000086 Extended Warranty: 994-000139 (1 year), 994-000170 (3 year)	

logitech[®]

www.logitech.com/RoomMate

Contact your reseller or contact us at www.logitech.com/vcsales

Logitech Americas

7700 Gateway Blvd. Newark, CA 94560 USA

Logitech Europe S.A. EPFL - Quartier de l'Innovation Daniel Borel Innovation Center CH - 1015 Lausanne

Logitech Asia Pacific Ltd. Tel: 852-2821-5900 Fax: 852-2520-2230

 $\hbox{@}$ 2021 Logitech. Logitech, the Logitech logo and other Logitech marks are owned by Logitech and may be registered. All other trademarks are the properties of their respective owners. Logitech assumes no responsibility for any errors that may appear in this publication. Product, pricing and feature information contained herein is subject to change without notice.

Published November 2021